



Transformer 2X12V300

INSTALLATION PROCEDURES

Installation Notes

Each transformer is supplied with a dished washer and protection pads for single fixing hole.

Ensure that the pads are fitted above and below the transformer winding and that the dished washer is on top of the upper pad.

Do not over tighten the fixing bolt (not supplied) as this could damage the winding.

Under no circumstances should both ends of the fixing bolt contact a metal chassis or frame as this would create a short causing irreparable damage.

Allow extra 4 mm for mounting kit and allow extra 5 mm where leads emerge



240 Volt

Yellow

Yellow

0 Volt

12V / 12.5A — Green

0 V — Red

12V / 12.5A — Brown

0 V — Blue

For 12 Volt operation: Join the **RED** and **BLUE** wires for one connection and the **GREEN** and **BROWN** wires for the other connection

For 24 Volt operation: Join the **GREEN** and **BLUE** wires and the connections for 24 Volt are the **RED** and **BROWN** wires.